


ESS-ES1869

DEVICE DRIVER INSTALLATION Under **WINDOWS NT 4.0**


August 1997

ES1869 Device Driver Installation Guide for Windows NT 4.0


- 12) Start the Windows NT 4.0 system. Log on as Administrator and insert your CD title into your CD-ROM drive.
- 13) Click the **Start** button, point to **Settings** and select the **Control Panel** group. Double click the **Multimedia** icon and you should see a figure as shown below. Please click the **Devices** tap to continue.




- 14) Please click the **Add** push button in the figure, as shown on the next page.




15) In the "Add" dialog box, choose **"Unlisted or Updated Driver"** and click the "OK" push button.




16) An "Install Driver" dialog box will appear. Please specify the driver path as **"D:\NT40"** and click the "OK" push button.




17) Windows NT will find the drivers as shown in the figure below. Please click the "OK" push button to continue.




18) The setup program will ask you to choose the ESS base I/O address. Please choose an appropriate one and click the "Continue" push button to continue.




19) In the figure shown as below, you will have to specify the system resources. Make sure that your choice does not get in conflict with other hardware configurations.




- 9) In the "System Setting Change" dialog box, you can choose either **"Don't Restart Now"** to setup the Gameport Joystick" or **"Restart Now"** for the new sound card driver to take effect.




- 20) To install the Gameport Joystick, please insert your Windows NT4.0 CD-ROM into your CD-ROM drive. Repeat step 2) to 4). In the "Install Driver" dialog box , specify the driver path as **"D:\drvlib\MULTIMED\JOYSTICK\X86\"** and click the "OK" push button.




- 21) An **Analog Joystick Driver** will be found in the "Add Unlisted or Updated Driver" dialog box. Please click the "OK" push button to continue.



In the "Microsoft Joystick Configuration" dialog box, please choose the I/O address and click the "OK" push button.



22) In the "System Setting Change" dialog box, you can choose either "Don't Restart Now" to go on with your tasks, or "Restart Now" for the new Gameport Joystick driver to take effect.



E-20-022
Version 1.0